

### Remarks

This Preliminary Amendment cancels, without prejudice, claims 1-9 in the underlying PCT Application No. PCT/DE03/01601 and adds new claims 10-18. The new claims, inter alia, conform the claims to United States Patent and Trademark Office rules and do not add any new matter to the application.

In accordance with 37 C.F.R. § 1.125(b), the Substitute Specification (including Abstract) contains no new matter. The amendments reflected in the Substitute Specification (including Abstract) are to conform the Specification and Abstract to United States Patent and Trademark Office rules or to correct informalities. As required by 37 C.F.R. §§ 1.121(b)(3)(ii) and 1.125(c), a Marked-Up Version of the Substitute Specification comparing the Specification of record and the Substitute Specification also accompanies this Preliminary Amendment. Approval and entry of the Substitute Specification (including Abstract) are respectfully requested.


The underlying PCT Application No. PCT/DE03/01601 includes an International Search Report, dated September 18, 2003, a copy of which is included. The Search Report includes a list of documents that were considered by the Examiner in the underlying PCT application.

Applicants assert that the subject matter of the present application is new, non-obvious, and useful. Prompt consideration and allowance of the application are respectfully requested.

Respectfully Submitted,

KENYON & KENYON

Dated: 3/22/05

By:   
Richard L. Mayer  
(Reg. No. 22,480)

One Broadway  
New York, NY 10004  
(212) 425-7200

## MICROWAVE OSCILLATOR

### Background Information Field Of The Invention

The present invention relates to a microwave oscillator having a hollow conductor, an oscillation generator which is mounted on a heatsink and projects into the hollow conductor, and a printed circuit board having electronic components for supplying  
5 direct current voltage to the oscillation generator.

### Background Information

Microwave oscillators based on planar technology are known in which the oscillation generator and conductor structures for forming resonators, microwave conductors, filters, and the like are situated on a common substrate. However, for specific  
10 applications, e.g., a distance warning radar in motor vehicles, microwave oscillators based on hollow conductor technology are preferred, so that it is possible to satisfy the requirements for quality and performance of the oscillator.

A microwave oscillator known from the related art for a motor vehicle distance  
15 warning radar has a hollow conductor or oscillator body in the form of a metallic housing, which is screwed onto the radar device and is electrically connected by hand soldering using a lead. The oscillation generator is formed by a Gunn device, which projects into the oscillator body from below. The upper end of the oscillator body is closed by an insulating body to which a printed circuit board is attached. The  
20 Gunn device is supplied with direct voltage by a pin-like filter element, known as a bias choke, which extends from the printed circuit board through the interior of the oscillator body to the top of the Gunn device and acts as a lowpass filter. The printed circuit board includes a capacitive network, which is used to suppress voltage spikes when switching the oscillator on and off.

### Object, Achievement, and Advantages of the Summary Of The Invention

~~The~~An object of the present invention is to ~~devise~~provide a microwave oscillator of the type described above, which has a compact design and which may be manufactured and mounted in a more simple manner.

30 This objective is achieved in that the printed circuit board forms one wall of the hollow conductor and that the oscillation generator and its heatsink are embedded in the printed circuit board.

Because in this design, the oscillation generator, a Gunn device, for example, is attached directly in or on the printed circuit board, which also supports the circuit components for the supply of direct voltage to the Gunn device, it is not necessary for a pin-like bias choke to be mounted in the interior of the hollow conductor, and the production of the hollow conductor and the assembly of the printed circuit board and of the Gunn element are efficiently combined into a single operation. Because the heatsink, which supports the Gunn device, passes through the printed circuit board, the heat loss arising during operation of the Gunn device is effectively dissipated to the outside. In the area of the printed circuit board, the electrically conductive envelope of the hollow conductor may be formed by metallic coating of this printed circuit board or optionally by a metallic base plate, which is in contact with the printed circuit board.

~~Advantageous embodiments of the invention are described in the dependent claims.~~

In the oscillator of the present invention, the lowpass function of the conventional bias choke is preferably performed by a conductor structure, which is formed on the printed circuit board and is a part of the electrical feed to the Gunn device.

The microwave output of the oscillator is preferably formed by a stripline formed on the printed circuit board, the stripline being guided out of the hollow conductor and coupled to the microwave field within the hollow conductor.

In one embodiment, the hollow conductor is expanded to form a resonator chamber at the site of the Gunn device. In this way, it is possible to form a harmonic wave resonator, the fundamental wave of which is attenuated in the hollow conductor on the way from the resonator chamber to the coupling point of the stripline. The frequency may be tuned in a known manner using a tuning pin in the resonator chamber. In another embodiment, the tuning is performed in a known manner by rotation and/or vertical displacement of a resonator disc, which projects into the hollow conductor in a position diametrically opposite the Gunn device.

For an adjustment of power between the hollow conductor and the Gunn device, a choke piston is provided, which is situated slidably between the top wall of the hollow conductor and the lower wall formed by the printed circuit board.

#### Brief Description of the Of The Drawings

~~Exemplary embodiments of the present invention will be explained in greater detail below with reference to the drawings.~~

Figure 1 shows a schematic sectional representation of the microwave oscillator according to a first embodiment;

Figure 2 shows a top view of a part of a printed circuit board of the microwave oscillator according to Figure 4; and

- 5 Figure 3 shows a sectional representation of a microwave oscillator according to a second embodiment.

#### Detailed Description of the Exemplary Embodiments

10 The microwave oscillator shown in Figure 1 has a metallic base plate 10, on which a printed circuit board 12 is in planar contact. Embedded into printed circuit board 12, the thickness of which is exaggerated in the drawing for reasons of clarity, is a heatsink 14 in the form of a copper block, which is in thermal and electrical contact with base plate 10. Situated on the top of heatsink 14 is an oscillation generator 16, which is formed here by a Gunn device. The lower electrode of the Gunn device is  
15 grounded via heatsink 14 and base plate 10.

An electrically grounded metallic housing 18, which together with printed circuit board 12 or associated base plate 10 borders a hollow conductor 20, arches over oscillation generator 16. At the position of oscillation generator 16, hollow conductor 20 is expanded to form a resonator chamber 22.

20 Outside of hollow conductor 20, electronic components 24 are situated on printed circuit board 12, these components being a part of a circuit for supplying oscillation generator 16 with direct voltage. For example, components 24 are capacitors, which are used to suppress voltage spikes when the oscillator is switched on and off. Oscillation generator 16 is supplied with direct voltage via a conductive structure 26  
25 formed on printed circuit board 12, the conductive structure shown being connected to the upper electrode of the Gunn device via a bonding wire 28.

When a direct voltage is applied to oscillation generator 16 in this manner, the oscillator is excited to produce electronic oscillations based on the Gunn effect, for example, with a basic frequency of 38 GHz. Resonator chamber 22 is tuned to this  
30 basic frequency so that standing electromagnetic waves are excited in resonator chamber 22 using this basic frequency and its harmonics. A tuning pin 30, which projects into resonator chamber 22, is provided for the precise frequency tuning.

Hollow conductor 20 is dimensioned in such a way that it allows the first harmonic wave having a frequency of 76 GHz to pass, yet attenuates the fundamental wave. One part of the oscillation energy of the first harmonic wave is thus diverted via hollow conductor 20 and at a certain distance from resonator chamber 22 is coupled into a stripline 34 via a resonator 32 designed in the manner of an antenna patch, the stripline being guided out of hollow conductor 20 and forming the microwave output of the oscillator. The distance between resonator 32 and resonator chamber 22 is selected in such a way that the fundamental wave decays before it reaches resonator 32.

- At the end diametrically opposite stripline 34, hollow conductor 20 is closed by a choke piston 36, which is used to adjust the power between hollow conductor 20 and oscillation generator 16. At least in the area of choke piston 36, the top of printed circuit board 12 has a metallic coat 38 which is connected to base plate 10 by printed circuit board 12 in a plurality of locations so that choke piston 36 is in electrical contact with base plate 10. Optionally, the bottom or the interior of printed circuit board 12 may also have a continuous metallic coating, which is not shown here and which instead of base plate 10, forms the electrical boundary of hollow conductor 20 and is simultaneously used as a shell electrode for stripline 34 and conductive structure 26.
- As Figure 2 shows, conductive structure 26 forms a lowpass filter 40, via which the direct voltage component of the oscillator is screened against high-frequency oscillations.

The exemplary embodiment shown in Figure 3 differs from the exemplary embodiment of Figure 1 in that chamber 22 is omitted. Instead, a rotatable and height-adjustable resonator disc 42 for frequency tuning is attached to the lower end of tuning pin 30.

Abstract Of The Disclosure

5 A microwave oscillator having a hollow conductor ~~(20)~~, an oscillation generator (46) which is mounted on a heatsink ~~(14)~~ and projects into the hollow conductor ~~(20)~~, and a printed circuit board ~~(12)~~ having electronic components ~~(24)~~ for supplying direct voltage to the oscillation generator ~~(16)~~ is described. The printed circuit board ~~(12)~~ or a metallic coating on, in, or under this printed circuit board forms one wall of the hollow conductor ~~(20)~~, and the oscillator ~~(16)~~ including its heatsink ~~(14)~~ is located in the printed circuit board ~~(12)~~.

~~(Figure 1)~~